

RE3-ACC-CXUF Rear to front mount antenna cable kit

- Two high-quality RG-58 50 Ω coax cables
- Female flange mount BNC on one end for panel mounting
- Male BNC on other end couples to receiver antenna input jack



The CXUF is a pair of high quality, low-loss coax cables intended to relocate a wireless receiver's antenna input jacks to the front panel of a 19" rack. The threaded flange mount connectors fit securely into the openings of either the RMK1 or RMK2 rack mounting kits for front-mounting the stock $\frac{1}{2}$ wave antennas or extension coax cables. The male BNC twist-on connectors on the other ends securely connect to the receiver's antenna A and antenna B RF input jacks.


Technical specifications

Cable type:	Coaxial
Impedance:	50 Ω
Length:	1 meter
Connector types:	Male BNC twist-on on one end Female BNC threaded flange mount on the other end
Color:	Black
Net weight:	2 oz. (57 g)
Gross weight:	2.1 oz. (61 g)

Installation/configuration notes

To install the antenna cables, do the following:

1. Ensure the receiver is securely mounted with RMK1 or RMK2 rack kit.
2. Remove the locking nut, lock washer, and rubber insulator from the CXUF threaded flange-mount connector.
3. While aligning the flat (A) portion of the threaded connector barrel with the flat portion of the rack ear front flange opening, slide the threaded barrel through the opening until it is fully extended through the rack ear flange. (RMK2 rack ear used for illustration.)
4. Slide the rubber insulator ring onto the threaded connector barrel.
5. Slide the lock washer onto the threaded connector barrel.



2 | RE3-ACC-CXUF Rear to front mount antenna cable kit

6. Thread and tighten the nut onto the threaded connector barrel.
Ensure the nut is tightened securely to the connector barrel.
7. Repeat steps 4-7 for the other cable and rack ear.
8. Connect the other ends of the antenna cables into antenna A and antenna B inputs of the receiver, or an antenna distribution device such as the RE3-ACC-AASP active antenna splitter or RE3-ACC-PASP passive antenna splitter.

Compatible products

Order number	Description
RE3-ACC-RMK1	Rack mount kit for single RE3 receiver
RE3-ACC-RMK2	Rack mount kit for two RE3 receivers
RE3-ACC-CXU2	2 foot antenna coax cable (pair)
RE3-ACC-AASP	2-in x 8-out antenna splitter 470-960MHz

Parts included

Quantity	Component
2	CXUF cables
2	Nuts
2	Lock washers
2	Rubber insulator rings
1	Engineering datasheet
1	Warranty and product documentation information card

Ordering information

RE3-ACC-CXUF Rear to front mount antenna cable kit
BNC to BNC 50Ω rear to front-mount antenna coax cable kit, black
Order number **RE3-ACC-CXUF**

Represented by:

Germany:
Bosch Sicherheitssysteme GmbH
Robert-Bosch-Ring 5
85630 Grasbrunn
Germany

Bosch Security Systems, Inc.
12000 Portland Avenue South
Burnsville MN 55337
USA

www.electrovoice.com